

## FCSL1000 SERIES - INSTALLATION INSTRUCTIONS

CAUTION: BEFORE CONNECTING THE FIXTURE TO A POWER SUPPLY, MAKE SURE THE POWER IS SWITCHED OFF.

Includes : SL1012, SL1013, SL1014, SL1015

**NOTE:** For Single Gang Box Installation



**FC**   
OUTDOOR LIGHTING  
800.900.1730  
3609 Swenson Ave.  
St. Charles, IL 60174

### GENERAL:

1. Luminaire must be installed by licensed electrician.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code.
3. Before starting the installation, make sure all electricity has been turned off and electrical breaker has been locked out and tagged out.
4. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.

**NOTE:** The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur.

### INSTALLATION INSTRUCTIONS:

- 1) Remove the Mounting Plate from the back of the step light by unscrewing the Set Screw from the bottom of the faceplate. See FIG. A. Then make the wiring connections at the J-Box.
- 2) Use J-Box Mounting Screws to fasten the Mounting Plate to the J-Box on the intended surface, See FIG. B. It mounts to a standard sized J-Box. **NOTE:** Position Weep Hole to bottom.
- 3) Reattach the faceplate to the mounting plate using bottom Set Screw. Tighten to ensure luminaire is level and secure.
- 4) For exterior applications, **installer must silicone caulk** the outer edge of the luminaire that comes in contact with the mounting surface.  
**IMPORTANT:** Do not caulk over weep hole opening in bottom of faceplate, this is critical for a secure and reliable installation.
- 5) Restore power to circuit then test luminaire.

**NOTE:** LED lamping is integral and NOT intended for general servicing.

**NOTE:** Luminaires are listed for installation with liquid tight or rigid wall conduit only. Luminaires installed without a silicone bead will void the warranty.

### DETAILED ILLUSTRATION

